

# INDOOR WIRELESS IR CAMERA

## ADC-V522IR



### OVERVIEW

Crystal-clear 1080p HD video, infrared night vision and secure cloud recording make the ADC-V522IR Wi-Fi Video Camera from Alarm.com ideal for indoor video monitoring. With its compact design and flexible mounting options, the ADC-V522IR is easy to install – whether mounted on a wall or ceiling, or simply placed on a shelf.

### FEATURES

- HD 1080p video
- IR night vision

### INCLUDED ACCESSORIES

- Wi-Fi Video camera
- Camera stand
- Quick Installation Guide
- Mounting hardware
- Power adapter

### SPECIFICATIONS

<b>Maximum resolution</b>	1920x1080
<b>Recording compression</b>	H.264, MPEG-4
<b>Image sensor</b>	1/2.9" CMOS, 2.12 MP, 1920x1080
<b>Lens</b>	2.8 mm, F1.85
<b>Angle of view</b>	113°
<b>Low-light sensitivity</b>	0 lux with IR
<b>IR range</b>	Up to 5 meters (~15 feet)
<b>Image adjustments</b>	Flip, brightness, contrast, saturation, sharpness
<b>Video motion detection</b>	3 windows, adjustable sensitivity and threshold
<b>Wireless connectivity</b>	802.11 b/g/n/ac, 2.4 & 5 GHz
<b>Ethernet connection</b>	10/100Mbps RJ-45
<b>Simultaneous viewers</b>	10
<b>Operating temperature</b>	0°C – 40°C (32°F – 104°F)
<b>Operating humidity</b>	20%-80% (non-condensing) RH
<b>Max power consumption</b>	12 V DC, 5 W
<b>Dimensions (WxH)</b>	2.75" x 2.06" x 3.67"

### LED Guide

	LED Status	Description
Install	All off	Power off
	Solid <b>Red</b>	Power on, system booting
	<b>Green</b> blink every second	Local network connection with local IP address
	Solid <b>Green</b>	Full internet connection with Alarm.com IP
	Blinking <b>Blue</b>	WPS connecting in progress
	Blinking <b>White</b>	Wi-Fi access point mode
Trouble Conditions	Solid <b>Red</b>	No local or Internet connection
Factory Reset	<b>Red</b> blink every 0.15 second + <b>Green</b> blink every 0.15 second	Restoring factory default settings